DEG. / DIV.	A	B	C	D	ANGLE	
0~5	±0.02	±0.05	±0.1	±0.2	0~30°	±0.1°
5~10	±0.05	±0.1	±0.15	±0.5	31°~60°	±0.3°
10~50	±0.1	±0.15	±0.2	±0.5	61°~90°	±0.5°
50~500	±0.15	±0.2	±0.25	±0.5		
500~	±0.15%	±0.2%	±0.25%	±1.0		

版次	修改内容	修改	审核	批准	日期
A0	第一次发行				

SOPRO
POWERED BY ORVIBO

S20 Ultra-thin Magnetic Track Power Supply

User Manual

Product Description

S20 Ultra-thin Magnetic Track Power Supply is a special power supply suitable for the blade ultra-thin magnetic suction series. It has the advantages of small size, stable output and convenient installation.

Product List

S20 Ultra-thin Magnetic Track Power Supply x1 | Power Connector x1 | Screw x3 | Rubber Plug x3 | User Manual x1

1

Installation Instructions

① Be sure to cut off the power before installation, and strictly follow the instructions.
② It is recommended to install by a professional electrician, and no live operation is allowed.
③ Do not use in humid environments such as outdoors or bathrooms.

Installation Guide

2

①

3

②

4

③

5

Please turn off power at circuit breaker before installation!

① After passing the reserved wires through the power accessories threading holes, fix the power accessories with screws (note that the outlet position needs to be designed in advance), and install the rails at both ends after installing the accessories.
② Slide out the power cover on one side of the power supply to expose the terminal, and connect the reserved wire to the terminal.
③ Complete the wiring, press and hold the mounting clip on one side of the power supply, and install the power supply vertically into the track. (Pay attention to the buckle position on the power supply and the power supply accessories)
④ Push the power supply cover into the power wiring bayonet position to complete the installation.
⑤ Power on and ready to use.

6

Parameter

Product Model	DMN15120(White)/DMN15081(Black)
Product Size	370*30*32.6mm
Rated Power	150W
Operating Temperature	-20℃ — 50℃
Relative Humidity	20~90% RH
Rated Input	AC220~240V
Power Factor	0.9
Certification	CCC

7

Warranty Range And Duration

One year warranty applies to most ORVIBO product unless other wise specified at the time of purchase.
Accessories included with the main device and batteries have a warranty of six months when buying used in ORVIBO products, the product warranty remains measured from the time it was bought by the original owner.
Any other promises made by dealers beyond the guarantee of ORVIBO, ORVIBO will not assume any liability.
The following cases do not belong to free repair scope and ORVIBO will provide paid services. Please note.
Fill to provide warranty card and related sales invoices.
Cleaning of product and wear loss under normal circumstances (such as natural loss of casing, inserting compo-nents, aging andwear).

8

Any product failure or damage caused by installation, usage maintenance, and storage that are not in accordance with usage instructions.
Alter or tear up barcode on products or warranty card without authorization.For those beyond change or warranty period.
Product serial number or type on warranty card does not match the product itself.
Without getting the permission of ORVIBO, change its inherent structure circuit privately, or dismantling or modifying without authorization.
Product damage caused by accident, human abuse/misuse, such as output short circuit, high-voltage input, overload work, high temperat- ure, water inflow, mechanical damage, broken serious oxidation or rusty and etc.

9

Damage caused by transportation loading and unloading on the way of return for repair.
Product failure or damages caused by force majeure such as earthquake, fire, flood lightning and so on.
Product failure or damaged caused by any problem other than product design, technology, manufacturing, quality and others.
Accessories are not included in free repair scope.
This regulation shall come into effect since the issuing date. ORVIBO will keep the final interpretation right and revise.

10

Shenzhen ORVIBO Technology Co., Ltd.
7F, Block A7, Nanshan I Park, No.1001
Xueyuan Road, Nanshan District,
Shenzhen, 518055, PRC
www.orvibo.com
support@orvibo.com

备注:

1. 展开尺寸：152*348(mm) ,5折页
2. 材质：80克书纸
3. 印刷：黑色双面印刷
4. 线框为折痕位

未注公差：		制图	审核	批准	产品名称	刀锋超薄磁吸轨道电源 S20 英文说明书	材料	80g书纸
≤10mm	±0.05mm	周宇婷			产品料号	3.06.010XXX	版次	V0.1
≤50mm	±0.1mm							
>50mm	±0.2mm							
单位	mm							
	日期	16-June-22						

ORVIBO
TEL:+86-0755-85277097
FAX:+86-0755-85277087
深圳市欧瑞博科技股份有限公司
SHENZHEN ORVIBO TECH CO.,LTD.